


10 GA WIRE  
SEW

#6073 FUSE BLOCK (2 EA)  
600V 30A 3P  
USES (6) 30A  
CLASS CC FUSES #6076-1



**WIRE SIZES**

NOTE: ALL WIRES TO BE  
TYPE SEW/SF2, #10 AWG  
MINIMUM UNLESS NOTED

**CONTROL WIRING NOTE**

ALL CONTROL WIRES  
#20 AWG #4609  
UNLESS OTHERWISE NOTED




**POWER REQ'TS**

208 VOLTS  
1 PHASE  
60 HERTZ  
79 AMPS  
16432 WATTS

#6311  
30A RELAY  
208-240V  
COIL  
DPST-NO

**CAUTION**

TO PROVIDE CONTINUED  
PROTECTION AGAINST THE  
RISK OF ELECTRIC SHOCK,  
CUSTOMER'S POWER  
SUPPLY MUST BE  
PROPERLY GROUNDED.



#20 GA  
#4609

#6344-1  
CONTROL  
POWER  
ON/OFF  
SWITCH  
10AMP 240V

#6355  
30A RELAY  
W/12V  
DC COIL

TYPE K T/C  
6750-2

#6060-1  
#22GA WIRE  
MULTI-COND

#6778-CONTROL  
TRANSFORMER  
OUTPUT=24VAC

FUSE  
#6726  
1/2 AMP

SENTRY 2.0  
CONE FIRE

TO RE-ORDER ELEMENTS, SPECIFY		
DESCRIPTION	QTY	LDC
EL 704111BASTB	4	SIDE-TOP/BOT
EL 704111BASM	2	SIDE-MID

T/C EXT WIRE

UL/CUL LISTED

2350°F

REV	DATE	BY	DESCRIPTION
-	02-14-01	RLG	
A	12/02/02	ITB	MOVED FUSE TO TRANS LEAD
B	6/2/03	ITB	MOVED SW TO CENTER RELAY

SWITCH BOX ASSY-40986-2

PARAGON INDUSTRIES  
2011 SOUTH TOWN EAST BLVD  
MESQUITE, TEXAS 75149

**WIRING DIAGRAM**

208V, 1 PHASE, 60HZ, 16432W

PART NO.	REV
704111BA00	B
DRAGON 242724	